

Apollo Discovery Heat Detector

Part No. **58000-400APO**



Overview

- A high specification programmable heat detector.
- Fully compatible with C-TEC's XFP & ZFP XP95/Discovery Addressable Fire Panels.
- User programmable to operate in one of five sensitivity modes (e.g. Mode 1 will give a higher sensitivity to fire than Mode 5).
- Uses a single thermistor to sense the air at the detector position.
- Ideal in environments that are dirty or smoky under normal conditions such as warehouses, loading bays and car parks.
- Remote test feature.
- Red LED illuminates when the detector is in alarm.
- Certified to EN54-5 by the LPCB.
- Requires a 45681-210APO standard base or 45681-242APO low power relay base.
- 'Xpert' card addressed for speedy installation.

Technical Specifications

Approvals/certifications	Certified to EN54-5 by the LPCB
Compatibility	Compatible with C-TEC's XFP/ZFP XP95/Discovery Addressable Fire Panels.
Application/operation	Uses a single thermistor to sense the air temperature at the detector position. Provides a very good response in environments that are dirty or smoky in normal conditions.
Application temperature	n/a
Static response temperature	n/a
Sensitivity	Option to select 5 different operating modes at the fire panel. See Operation Modes tab below for details.
Supply wiring	2-wire, polarity insensitive.
Supply/operating voltage	17 to 28V DC.



Quiescent current	350µA.
Alarm current	3.4mA (LED illuminated).
Indicators	2 clear LEDs emitting red light when in alarm. Optional remote LED.
Connections	L1&L2 supply in/out; +R remote LED +Ve connection; -R remote LED -Ve connection. (5mA max. remote LED current @ 5V measured across remote load).
Product dimensions (mm)	100mm diameter x 42 mm H (not in base). 50mm height when in base.
Construction & finish	White polycarbonate UL94-VO. Nickel plated stainless steel terminals.
IP Rating	IP44.
Weight	105g (not in base); 160g (in base).
Operating conditions/temperature	-40°C to +80°C.
Notes	Requires a BF308XP standard base or BF308XPR low power relay base. 1mA power up surge current for 0.3 seconds.

