

AlarmSense Base Sounder/Visual Indicator

Part No. **45681-509APO**



Overview

- Will accept any AlarmSense fire detector to provide fire detection and an audible AND visual alarm warning signal at the same point.
- 70d-87dB(A) sound output (visual indicator activates with sounder).
- Certified to EN54-3 by UL International (UK) Limited.
- Suitable for use with C-TEC's CFP AlarmSense range of 2-8 Zone Two-Wire Fire Panels.
- AlarmSense priority/non priority signal recognition
- Detects the removal of a detector head and reports a fault
- Continues to work during unauthorised removal of detector.
- High and low volume ranges.
- Red and white caps available for stand-alone use.
- Can also be purchased as part of a detector/sounder visual indicator base combination (see Combination AlarmSense Devices section below).

More Information

Technical Specifications

Approvals/certifications	Certified to EN54- by by UL International (UK) Limited.
Application/operation	Designed to be ceiling mounted with an AlarmSense fire detector. Red and White caps available for stand alone use.
Supply wiring	2-wire monitored, polarity insensitive.
Supply/operating voltage	18-33VDC (sounders active); Less than 15VDC (sounders off).
Quiescent current	Less than 20µA @ 12VDC.
Nominal SPL (Sound Pressure Level)	87dB(A) max (high volume setting); 70dB(A) nominal (low volume setting).



Alarm current	5mA (sounder active current at 24V).
Product dimensions (mm)	115mm diameter x 40mm deep (without optional AlarmSense detector).
Construction & finish	White/clear polycarbonate. Red and white caps available for stand alone use.
IP Rating	TBC.
Weight	150g



T 01942 322744 E sales@c-tec.co.uk
F 01942 829867 W www.c-tec.com



C-TEC, Challenge Way, Martland Park, Wigan, WN5 0LD United Kingdom